

The Vista I3

Control Console.



A revolution in lighting in one compact package.

The I3 is an incredibly compact and powerful lighting console that provides the software, the processor and the control elements of the Vista console. All you have to do is connect a screen, keyboard and mouse and you've got a fully operational Vista with exactly the same software and feature set as the full-size console.

You can attach two external monitors and, if you like to work with a pen-tablet, you can plug it in as the main monitor. The four DMX outputs give you plenty of connections to lights and dimmers and you can also connect Artnet or Pathport compatible devices through the Ethernet port.

The I3 features a 'dongle' that determines the number of channels available: you can choose whether you want 128, 256, 512, 1024, 2048 or 8192 channels, simply by choosing the 'dongle' that's best for you.

The I3 gives you all the features that make the Vista such a great live desk: big, clear LCDs, fader banks you can split or combine and a set of modifier buttons. With 20 playbacks (10 with faders), four DMX outputs, timecode input and three encoder wheels, you'll have all the control you need.



Feature List

Main Controls

- 5 user configurable function buttons
- Blue, Green, Yellow, Red modifier buttons
- Power button
- Grand Master (rotary) fader and DBO button

Playback Controls

- 20 Playbacks, 10 with faders and flash buttons, 10 without
- Playbacks feature; Blue / White LCD, Select and Go buttons
- Split mode allows control of up to 50 Cuelists
- Playbacks can be configured for control of Groups, Presets and more
- Page Up / Down buttons

Super Playback Controls

- Playback with 2 faders and buttons
- Go, Pause, Back, Skip Forward, Skip Reverse, Skip to Start, Skip to End buttons
- Utilises LCD and Encoder wheels for display and real time control of playback and other advanced functions.

Programming Controls

- 3 Encoder Wheels with associated Blue / White LCD
- Next / Previous buttons
- 12 context sensitive function buttons

DMX Output

- DMX output channels determined by dongle – sold separately
- 128, 256, 512, 1024, 2048 or 8192 channel versions available
- Specify requirements at time of purchase
- Upgrades available

Input and Output Connections

- 4 DMX outputs (* Actual DMX output channels determined by dongle. Software pack, including dongle, must be purchased separately.)
- 7 USB2 connectors
- Linear Time code input †
- MIDI in/thru/out †
- Desk lamp outlet

Specifications

- Dimensions (w d h) : 650(mm) 600(mm) 170(mm)
- Weight : 19kg Net 25kg Shipping

System Requirements for the Vista application:

- Processor – Intel Core 2 Duo 2.13GHz
- System RAM – 1GB
- Hard Drive – 160GB SATA II
- Monitor Outputs – One DVI + One VGA, Independent
- DMX Outputs – Four ANSI E1.11
- USB Ports – Seven USB2.0

† Not implemented in V2.0



www.jandsvista.com

